

Moving Lights	Watt Draw	Amp Draw	Weight	Other	Moving Lights	Channels	Mode	Other
1915 Wash	400w	3.5a	26lbs		1915 Wash	35ch	Extended w/ Macro	21ch - Standard
3610 Wash	400w	3.5a	21lbs		3610 Wash	16ch	Standard	
1061 Wash	650w	5.5a	54lbs		1061 Wash	17ch	Standard	30 - Extended w/ Ring CTRL
BWS 440	570w	4.75a	49lbs		BWS 440	26ch	Standard	
LED Beam	120w	1a	8lbs	can jump up to 10 together	LED Beam	10ch		
Beam 200	350w	3a	38lbs		Beam 200	18ch	Standard	
Platinum Spot	350w	3a	29lbs		Platinum Spot	17ch	Standard	

LED Fixtures	Watt Draw	Amp Draw	Weight	Other	LED Fixtures	Channels	Mode	Other
LED Blinder	250w	2a	15lbs	links through IP65 connection	LED Blinder	4ch	4A	
Opti Tri 30	30w	0.25a	5.5lbs		Opti Tri 30	7ch	6.x.x.x	
Flat Par Tri 7	25w	0.25a	7lbs	links through IEC	Flat Par Tri 7	7ch		
Elation Opti Par	70w	0.50a	11lbs		Elation Opti Par	7ch	6.x.x.x	
Prestige Opti Par	80w	0.50a			Prestige Opti Par	8ch		
Mega Tri Bar	102w	1a	14lbs	links through IEC connection	Mega Tri Bar	7ch	P-5	
Prestige LED Bar	110w	1a		links through IP65 connection	Prestige LED Bar	6ch	x.xx	
Wireless RGBAWuv	165w	1.5a		links through PowerCon	Wireless RGBAWuv	10ch		
IP65 Small	110w	1a		links through IP65 connection	IP65 Small	8ch		
IP65 Large	350w	3a		links through IP65 connection	IP65 Large	8ch		

Special FX	Watt Draw	Amp Draw	Weight	Other	Special FX	Channels	Mode	Other
Cryo Jet	100w	1a			Cryo Jet	1ch		
Geyser RGB	1,500w	12a	21lbs		Geyser RGB	8ch		
Atomic 3k Strobe	3,000w	20a	17lbs	33a Peak	Atomic 3k Strobe	4ch	Effects On	Dip 1,2,3,5 OFF. Dip 4 ON
IceFog Q (ColdFlow)	2,850w	24a	250lbs	needs 2 legs of power	IceFog Q (ColdFlow)	NO DMX	NO DMX	Manual Control over 5-pin
Chauvet Nimbus (slow)	1,500w	13a	29lbs Empty	using 1 heating element	Chauvet Nimbus (slow)	NO DMX	NO DMX	Manual Trigger
Chauvet Nimbus (fast)	3,000w	26a	75lbs Full	using 2 heating elements	Chauvet Nimbus (fast)	NO DMX	NO DMX	Manual Trigger

Conventional & Dimming	Watt Draw	Amp Draw	Weight	Other	Conventional & Dimming	Channels	Mode	Other
375w HPL	375w	3.5a	N/A		375w HPL			
575w HPL	575w	5a	N/A		575w HPL			
750w HPL	750w	6.25a	N/A		750w HPL			
S4 Leko	N/A	N/A	14lbs		Deco Par			
Deco Par	60w	0.50a	3lbs		"LOVE" Letters	1-4ch		Letters can be independent or linked
"LOVE" Letters	720w	6a		1.5a per letter	Elation 1ch Dimmer	1ch		
Elation 1ch Dimmer	1,200w	10a	2.5lbs	10a max	Leviton 1ch Dimmer	1ch		Needs 3-5 Adapter
Leviton 1ch Dimmer	1,800w	15a	2lbs	15a max	Elation 6ch Dimmer	6ch		
Elation 6ch Dimmer	3,600w	30a	7.5lbs	5a max per channel	Sensor Rack 24ch	24ch		Needs 3-5 Adapter
Sensor Rack 24ch	57,600w @ MAX	20a x24	162lbs	Feeder in & pass through				to reset Sensor Rack: HOLD Setup, PRESS Reset continue to hold setup until DEEP CLEAR appears select "YES" and click enter, wait for rack to reset